

# CASH VALVE E-55 SERIES PRESSURE REGULATORS

## SELECTION GUIDE

Example:	E55	C	W	S	B	B	01	-	D	1
<b>Model</b>										
<b>E55</b>	E55 valve w/ bronze body and spring chamber									
<b>Valve size</b>										
<b>C</b>	1/2"									
<b>D</b>	3/4"									
<b>E</b>	1"									
<b>F</b>	1 1/4"									
<b>G</b>	1 1/2"									
<b>H</b>	2"									
<b>Service</b>										
<b>W</b>	Water/air									
<b>Body style/connection style</b>										
<b>S</b>	Side inlet/side outlet - straight thru w/ NPT connections									
<b>B</b>	Side inlet/side outlet - straight thru w/ BSPT connections									
<b>Diaphragm material</b>										
<b>B</b>	Buna-N (water/air)									
<b>Seat material</b>										
<b>B</b>	Buna-N (water/air)									
<b>Variation</b>										
<b>01</b>	Standard									
<b>02</b>	Without strainer screen									
<b>Design revision</b>										
<b>(-)</b>	Indicates original design									
<b>Spring material</b>										
<b>D</b>	Steel									
<b>E</b>	SST									
<b>Spring range</b>	Refer to table below									

## STANDARD SPRING RANGES (psig)

Spring Material	Size	1	2	3	4	5
Steel	1/2", 3/4", 1"	15 - 50	25 - 80	50 - 110	75 - 195	100 - 250
	1 1/4", 1 1/2", 2"	15 - 25	20 - 50	40 - 100	75 - 150	---
SST	1/2", 3/4", 1"	10 - 35	20 - 75	75 - 125	125 - 175	75 - 250
	1 1/4", 1 1/2", 2"	20 - 70	50 - 150	---	75 - 200	150 - 300

VCTDS-00510-EN © 2016, 2021 Emerson Electric Co. All rights reserved 09/21. Cash Valve is a mark owned by one of the companies in the Emerson Automation Solutions business unit of Emerson Electric Co. The Emerson logo is a trademark and service mark of Emerson Electric Co. All other marks are the property of their prospective owners.

The contents of this publication are presented for informational purposes only, and while every effort has been made to ensure their accuracy, they are not to be construed as warranties or guarantees, express or implied, regarding the products or services described herein or their use or applicability. All sales are governed by our terms and conditions, which are available upon request. We reserve the right to modify or improve the designs or specifications of such products at any time without notice.

Emerson Electric Co. does not assume responsibility for the selection, use or maintenance of any product. Responsibility for proper selection, use and maintenance of any Emerson Electric Co. product remains solely with the purchaser.